

Laser Particle Sensor Module

PM2008



Description

PM2008 laser particle sensor module use light scattering principle, to measure and calculate the suspending particle number which is within unit volume on the air exactly. Then output particle mass concentration by mathematical algorithm and scientific calibration.

Working principle

Sampling by the internal pressure which occurs by fan, when sampling particles pass through light beam (laser), there will be light scattering phenomenon. Scattered light will be converted into electrical signal (pulse) via photoelectric transformer. The bigger particles will obtain stronger pulse signal (peak value). Through peak value and pulse value quantity concentration of particles in each size can be calculate. Thus, real-time measured data is obtained through measuring quantity and strength of scattered light.

Main features

- ✧ The smallest size of available measurement: $0.3\mu\text{m}$
- ✧ High accuracy, digital display prioritized
- ✧ High sensitive and quick response
- ✧ All metal shielding, good in antijamming capability
- ✧ Super Slim Design, height only 12mm
- ✧ Three types of optional signal output: UART_TTL, I2C, PWM


Application

- ✧ Air purifier, air quality monitor
- ✧ Ventilation system, air conditioner with purifying function
- ✧ Auxiliary product of consumer electronic products
- ✧ Environmental Monitoring
- ✧ Handheld Air Quality Detector

Table 1: Cubic particle sensor module specification

Particle size range	$0.3\mu\text{m} \sim 10\mu\text{m}$
Output result	Particle mass concentration ($\mu\text{g}/\text{m}^3$)
Maximum Measurement range	PM1.0: $0 \sim 1,000\mu\text{g}/\text{m}^3$ PM2.5: $0 \sim 1,000\mu\text{g}/\text{m}^3$ PM10: $0 \sim 1,000\mu\text{g}/\text{m}^3$
Test dust	Aerosol kcl.
Measurement (Reference)	GRIMM 11-A, TSI 8530
Resolution	$1 \mu\text{g}/\text{m}^3$
Maximum Consistency Error for PM1.0&PM2.5	$0 \sim 100\mu\text{g}/\text{m}^3, \pm 10\mu\text{g}/\text{m}^3$ $101 \sim 500\mu\text{g}/\text{m}^3, \pm 10\%$ reading
Maximum Consistency Error for PM10	$0 \sim 100\mu\text{g}/\text{m}^3, \pm 25\mu\text{g}/\text{m}^3$ $101 \sim 500 \mu\text{g}/\text{m}^3, \pm 25\%$ reading
Respond time	1sec
Time to first reading	≤ 8 seconds
Working temperature	$-10^\circ\text{C} \sim 60^\circ\text{C}$
Working humidity	$0 \sim 95\%$ RH (non-condensing)
Storage temperature	$-30^\circ\text{C} \sim 70^\circ\text{C}$
Power supply	DC $5\text{V} \pm 0.1\text{V}$, ripple wave $< 50\text{mV}$
Working current	$\leq 100\text{mA}$
Standby current	$\leq 200\mu\text{A}$
Digital output 1 (default)	I ² C, UART_TTL (L $< 0.8\text{V}$, H $> 2.7\text{V} @ 3.3\text{V}/5\text{V}$)
Digital output 2	PWM (customized)
Output method	Default by active output after powering on, sampling time interval should be over 1,000ms.
MTTF	37,297hr (continuous turn on)

Internal architecture description




Picture 1. Internal configuration

According to above Block Diagram, the light source of PM2008 is consist of fan for particle sampling, laser diode for particle detection, photodiode for scattered laser signal, Amp for signal amplification the detecting part is consist of light sensitive part which receives reflected light and amplifying circuit. Value and communication output is finished by MPU.

When heating resistor heats, and after showing vertical draft, particles will pass the detecting chamber. The light from laser diode will be scattered by particles and will be tell out by light sensitive equipment, then convert into electronic signal. Electronic signal is disposed by filter circuit and MCU, it will convert into PWM signal output.

Configuration structure and I/O definitions



Picture 2: Configuration structure and I/O definitions

Table 2: I/O definitions


No.	Pin	Description
1	VCC	Power input (+5V)
2	VCC	Power input (+5V)
3	GND	Power input (ground terminal)
4	GND	Power input (ground terminal)
5	Reset	Module reset signal (TTL level @3.3V/5V, Low level is reset)
6	NC	NC
7	RXD/SDA	UART-RX / PC SDA (TTL level @3.3V), compatible with 5V communication
8	CTL	Output mode exchange TTL level @3.3V High level or floating is UART communication mode, low level is PC communication mode
9	TXD/SCL	UART-TX / PC SCL (TTL level @3.3V), compatible with 5V communication
10	SET	TTL level @3.3V, high level or floating is normal working status, while low level is sleeping mode

Table 3. Connector description

Item	Pin spacing	Brand
JSD-BH-312-002	1.27 mm pitch	FXX


Typical application circuit

Case 1. UART application



Picture 3: UART application circuit

Case 2. I²C application




Picture 4: I²C application circuit

Note of circuit design :

- ※ UART and I²C communication is compatibility with 3.3V and 5V level.
- ※ There is pull-up resistor inside the SET and RESET. No matter there is signal input or not, these two pins will work normally. If they are not useful for you, keep it floating.
- ※ PIN6 is the pin for manufacturer testing, you can keep it floating.
- ※ The power supply of sensor should be 5V and low noise, please refer to table 1 for details.

Temperature influence curve




Picture 7. Temperature Influence Curve

Particle measured error: under $25 \pm 2^\circ\text{C}$, $0 \sim 1,000 \mu\text{g}/\text{m}^3$, consistency and accuracy of PM2.5 is either $\pm 10\%$ reading or $\pm 10 \mu\text{g}/\text{m}^3$, the bigger one is taken.

Temperature influence coefficient: $0.5\%/^\circ\text{C} \sim 1\%/^\circ\text{C}$ or $0.5 \mu\text{g}/\text{m}^3/^\circ\text{C} \sim 1 \mu\text{g}/\text{m}^3/^\circ\text{C}$, the bigger one is taken.


Sensor appearance size and installing



Picture 6: Appearance size (Unit mm, Error $\pm 0.2\text{mm}$)

Note of sensor installing

- ※ Metal case conducts with internal power supply. Notice that cannot short connect with other external circuit or chassis shell.
- ※ The surface of inlet and outlet cling to wall of user receiver, this is the best installing method. If cannot do like this, there should be air isolation structure between inlet and outlet, to avoid the air back flow in the user receiver.
- ※ The size of inlet and outlet for wall of user receiver should be smaller than inlet and outlet size of sensor.
- ※ For purification products, sensor cannot be installed in the purify air flue, if cannot do like this, should design a separately structure for sensor, make it isolated for purify air flue and sensor.。
For purifier and detector device, the install place of sensor should be above 20cm higher than floor, to avoid approaching the particles and floccules twine fan.
- ※ Sensor does not be recommended to use for outdoor detect equipment.
- ※ Sensor is an integral unit, in case of irreversible damage, sensor cannot be disassembling, including metal screening can.
- ※ When installing to system, make sure the inlet and outlet is unobstructed, and cannot be touched against by large air stream. There are two sides cannot be put downwards (As below pictures), In case of dust deposition on the surface of sensitive device, dust deposition will affect accuracy of sensor.



Communication protocol

The slaver extended command protocol

1, Master communication format

Feature bite1	Feature bite 2	Command bite	Status bite1	Status bite2	Check bite1	Check bite2
0x43	0x4d	CMD	DATAH	DATAL	LRCH	LRCL

2, Command and feature bite definition

CMD	DATAH	DATAL	Description
0xe2	X	X	Read value of passive
0xe1	X	00H-passive status 01H-active status	Status exchange
0xe4	X	00H-standby mode 01H-normal mode	Standby control

Reliability test

Test Item	Test Condition	Standard	Sample qty: N Defective qty: C
High temperature working	Leave the sensor in the ambient of $50\pm 2^{\circ}\text{C}$, powered with nominal voltage for 72 hours.	The sensor works normally after 2 hours in the ambient.	N=5, C=0
High temperature storage.	Leave the sensor in the ambient of $60\pm 2^{\circ}\text{C}$, powered with nominal voltage for 72 hours.	The sensor works normally after 2 hours in the ambient.	N=5, C=0
High temperature and high humidity operation	Operating the sensor in the ambient of $45\pm 2^{\circ}\text{C}$, $90\pm 5\%\text{RH}$, max voltage (within range of acceptable working voltage), for 72 hours.	The sensor works normally after 2 hours in the ambient.	N=5, C=0
Low temperature storage	Leave the sensor in the ambient of $-30\pm 2^{\circ}\text{C}$, for 72 hours.	The sensor works normally after 2 hours in the ambient.	N=5, C=0
Low temperature working	Leave the sensor in the ambient of $-10\pm 2^{\circ}\text{C}$, max voltage (within range of acceptable working voltage) for 72 hours.	The sensor works normally after 2 hours in the ambient.	N=5, C=0
Thermal cycle	Leave the sensor in ambient of -10°C for 1 hour then move it to ambient of $+50^{\circ}\text{C}$ for 1 hour. Keep this cycle for 10 times. No control of humidity, exert nominal voltage. No connection to inside power control, no connection to load, but adding voltage to direct current circuit.	The sensor works normally after 2 hours in the ambient.	N=5, C=0
Vibration test	10-55-10Hz/min, with amplitude of 1.5mm, vibrate in X, Y, Z direction, each direction for 2 hours.	The sensor works normally after 2 hours in the ambient.	N=2, C=0
Drop test	Drop the sensor from 70cm height down to the hard-wooden board randomly.	No damage, no breaking, no failure on electrical characteristics.	N=5, C=0
Salt spray test	According to GB/T2423.17-2008, leave the sensor in the 35°C salt-fog cabinet, spray it with 5% sodium chloride saltwater for 24 hours. Clean the sensor after test.	No red rust on the sensor surface.	N=5, C=0

Packing







Table 4. Packing description

Qty per layer	Layer	Carton	Carton dimensions	Packing material
55pcs	6 layers	330pcs	W400 * L300 * H320 mm	Red pearl cotton (ESD)

Ordering Information



After-sales services and consultancy

TEL: 86- 27-81628827 **FAX:** 86-27-81628821

ADD: Fenghuang No.3 Road, Fenghuang Industrial Park, Eastlake Hi-tech Development
Zone, Wuhan 430205, China

WEB: [Http://www.gassensor.com.cn](http://www.gassensor.com.cn)

E-mail: info@gassensor.com.cn